





# **MSR Electronics GmbH** Oberwilerstrasse 16

## 中国代理商:

宏科汽车技术研究中心

广州市五山华南理工大学国家科技园

2号楼 504-505室 邮编: 510640

电话: 020-38743030; 38743032;

020-38743233

传真: 020-38743233 sales@hkaco.com

www.hkaco.com

### Distributor:

# Air pressure sensors

The air pressure sensor is linked to the pressure system by means of the rapidaction coupling provided. The sensor is contained within a stainless steel casing and is connected to the MSR 12 via cable.

### P2500-4 AIR

Sensor type:	MS5534A
Measured parameters:	Pressure / temperature
Measurement range:	0-2500 mbar absolute -10°C to 60°C
Resolution:	1 mbar 1°C
Accuracy:	±2.5 mbar max. (at 750-1100 mbar absolute) ±1°C (at 20°C)
Item number:	B10130

### **P14K-3 AIR**

Sensor type:	MS5535A
Measured parameters:	Pressure / temperature
Measurement range:	0-14 000 mbar absolute -10 °C to +60 °C
Resolution:	1 mbar 1 °C
Accuracy:	±25 mbar max. (at 0-5000 mbar, 0°C to +50°C) ±160 mbar max. (at 0-14000 mbar, -10°C to +60°C) ±1°C at 20°C
Item number:	B10127

### **General**

Medium:	Air
Dimensions:	See drawing
Cable length:	1.6 m
Weight exc. cable:	52 G
Electrical connections:	Plug for MSR 12 (LEMO)
Power supply:	Via MSR 12
Material: Sensor housing:	Stainless steel
Operating conditions: Temperature: Humidity:	-10°C to +60°C 0-95% relative humidity, non-condensing
Storage conditions: Temperature: Humidity:	-20 °C to +70 °C 0-95 % relative humidity, non-condensing
Special feature:	Calibration coefficients stored in EEPROM
Required additional modu	ile: PR8 (Item number B10018)